

# SOT23 PNP SILICON PLANAR MEDIUM POWER TRANSISTORS


## BC807 BC808

ISSUE 4 – JUNE 1996

### PARTMARKING DETAILS

BC807 – 5DZ	BC808 – 5HZ
BC807-16 – 5AZ	BC808-16 – 5EZ
BC807-25 – 5BZ	BC808-25 – 5FZ
BC807-40 – 5CZ	BC808-40 – 5GZ

COMPLEMENTARY TYPES	BC807	–	BC817
	BC808	–	BC818



SOT23

### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	BC807	BC808	UNIT
Collector-Base Voltage	$V_{CBO}$	-50	-30	V
Collector-Emitter Voltage	$V_{CEO}$	-45	-25	V
Emitter-Base Voltage	$V_{EBO}$	-5		V
Peak Pulse Current	$I_{CM}$	-1		A
Continuous Collector Current	$I_C$	-500		mA
Base Current	$I_B$	-100		mA
Peak Base Current	$I_{BM}$	-200		mA
Power Dissipation at $T_{amb}=25^\circ\text{C}$	$P_{tot}$	330		mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150		$^\circ\text{C}$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector Cut-Off Current	$I_{CBO}$			-0.1 -5	$\mu\text{A}$ $\mu\text{A}$	$V_{CB}=-20\text{V}, I_E=0$ $V_{CB}=-20\text{V}, I_E=0, T_{amb}=150^\circ\text{C}$
Emitter Cut-Off Current	$I_{EBO}$			-10	$\mu\text{A}$	$V_{EB}=-5\text{V}, I_C=0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-700	mV	$I_C=-500\text{mA}, I_B=-50\text{mA}^*$
Base-Emitter Turn-on Voltage	$V_{BE(on)}$			-1.2	V	$I_C=-500\text{mA}, V_{CE}=-1\text{V}^*$
Static Forward Current Transfer Ratio	$h_{FE}$	100 40		600		$I_C=-100\text{mA}, V_{CE}=-1\text{V}^*$ $I_C=-500\text{mA}, V_{CE}=-1\text{V}^*$
	-16	100		250		$I_C=-100\text{mA}, V_{CE}=-1\text{V}^*$
	-25	160		400		$I_C=-100\text{mA}, V_{CE}=-1\text{V}^*$
	-40	250		600		$I_C=-100\text{mA}, V_{CE}=-1\text{V}^*$
Transition Frequency	$f_T$		100		MHz	$I_C=-10\text{mA}, V_{CE}=-5\text{V}$ $f=35\text{MHz}$
Collector-base Capacitance	$C_{obo}$		8.0		pF	$I_E=I_C=0, V_{CB}=-10\text{V}$ $f=1\text{MHz}$

\*Measured under pulsed conditions. Pulse width=300 $\mu\text{s}$ . Duty cycle  $\leq 2\%$   
Spice parameter data is available upon request for these devices



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.