


NPN SILICON PLANAR MEDIUM POWER DARLINGTON TRANSISTOR

BC372P

ISSUE 2 – SEPT 93

FEATURES

- * 100 Volt V_{CE0}
- * Gain of 8k at $I_C=250\text{mA}$
- * $P_{\text{tot}}=1$ Watt



E-Line
TO92 Compatible

ABSOLUTE MAXIMUM RATINGS.

| PARAMETER | SYMBOL | VALUE | UNIT |
|--|-----------------------|-------------|------------------|
| Collector-Base Voltage | V_{CBO} | 100 | V |
| Collector-Emitter Voltage | V_{CEO} | 100 | V |
| Emitter-Base Voltage | V_{EBO} | 12 | V |
| Peak Pulse Current | I_{CM} | 2 | A |
| Continuous Collector Current | I_C | 1 | A |
| Power Dissipation at $T_{\text{amb}}=25^\circ\text{C}$ | P_{tot} | 1 | W |
| Operating and Storage Temperature Range | $T_j; T_{\text{stg}}$ | -55 to +200 | $^\circ\text{C}$ |

ELECTRICAL CHARACTERISTICS (at $T_{\text{amb}} = 25^\circ\text{C}$).

| PARAMETER | SYMBOL | MIN. | TYP. | MAX. | UNIT | CONDITIONS. |
|---------------------------------------|----------------------|-----------|------|------|------|--|
| Collector-Base Breakdown Voltage | $V_{(BR)CBO}$ | 100 | | | V | $I_C=100\mu\text{A}$, $I_E=0$ |
| Collector-Emitter Breakdown Voltage | $V_{(BR)CES}$ | 100 | | | V | $I_C=100\mu\text{A}$, $I_B=0^*$ |
| Emitter-Base Breakdown Voltage | $V_{(BR)EBO}$ | 12 | | | V | $I_E=10\mu\text{A}$, $I_C=0$ |
| Collector Cut-Off Current | I_{CBO} | | | 100 | nA | $V_{CB}=80\text{V}$, $I_E=0$ |
| Emitter Cut-Off Current | I_{EBO} | | | 100 | nA | $V_{EB}=10\text{V}$, $I_C=0$ |
| Collector-Emitter Saturation Voltage | $V_{CE(\text{sat})}$ | | | 1.1 | V | $I_C=250\text{mA}$, $I_B=0.25\text{mA}$ |
| Base-Emitter Saturation Voltage | $V_{BE(\text{sat})}$ | | | 2 | V | $I_C=250\text{mA}$, $I_B=0.25\text{mA}$ |
| Static Forward Current Transfer Ratio | h_{FE} | 10K 8K | | | | $I_C=100\text{mA}$, $V_{CE}=5\text{V}^*$ $I_C=250\text{mA}$, $V_{CE}=5\text{V}^*$ |
| Transition Frequency | f_T | 100 | | | MHz | $I_C=100\text{mA}$, $V_{CE}=5\text{V}$ $f=100\text{MHz}$ |
| Output Capacitance | C_{obo} | | | 25 | pF | $V_{CB}=10\text{V}$, $f=1\text{MHz}$ |



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.