

Application Note

The CS5504 Family Characteristics

The CS5504/5/6/7/8/9 are a series of A/D converters all derived from a high performance $\Delta\Sigma$ architecture. The CS5504 family members are based on a core architecture including both an analog modulator and a digital filter, with only subtle differences between the individual products. The digital filter has been optimized to attenuate ac line interference (50/60 Hz and their harmonics) when the devices are operated from a low-cost 32.768kHz crystal.

The use of a low-cost 32.768kHz clock provides 20 samples per second from the family. The CS5505/6/7/8 can achieve up to 100 samples/second with a 163kHz system clock, while the CS5504/9 can achieve up to 200 samples/second when operated from its maximum input clock of 330 kHz. In achieving higher conversion rates, the CS5504 requires slightly higher operating currents than the CS5505/6/7/8. The CS5509 achieves the same high conversion rate as the CS5504 with lower power consumption, but pays a slight penalty in linearity.

Table 1 summarizes the similarities and differences of the CS5504 family.

The CS5504/9 come in smaller packages than the CS5505/6/7/8, however, the CS5505/6/7/8 have more functionality and flexibility. The CS5505/6/7/8 offer a sleep function, an on-chip voltage reference, and multiple serial communication modes.

Table 2 shows the CS5504 family's wide array of power supply options. Note: the CS5509 is single supply, however, the VA+ supply for all devices must always be the most positive operating voltage under all operating conditions, including start-up.

	VA+	VA-	VD+
CS5504/5/6/7/8	+5 to +10V	0V	+5V
	+5V	0 to -5V	+5V
	+5V	0 to -5V	+3.3V
CS5509	+5V	-	+5V
	+5V	-	+3.3V

Table 2. Power Supply Arrangements

	Resolution	#Channels	Max. Speed ³	Linearity ⁴ (Typical)	Sleep	Power	On-chip VREF	Serial Port Modes ⁵	Pin Count
CS5504	20-bits	2 ¹	200	0.0007%	No	4.4 mW	No	SEC	20
CS5505	16-bits	4 ²	100	0.0015%	Yes	3 mW	Yes	SEC, SSC	24
CS5506	20-bits	4 ²	100	0.0007%	Yes	3 mW	Yes	SEC, SSC	24
CS5507	16-bits	1 ¹	100	0.0015%	Yes	3 mW	Yes	SEC, SSC	20
CS5508	20-bits	1 ¹	100	0.0007%	Yes	3 mW	Yes	SEC, SSC	20
CS5509	16-bits	1 ¹	200	0.0015%	No	1.7 mW	No	SEC	16

Table 1. CS5504 Family Characteristics

- Notes:
1. Fully-differential
 2. Pseudo-differential
 3. CS5509 is production tested at 330 kHz (200 samples/second)
All others are production tested at 32.768 kHz for the best 50/60 Hz rejection.
 4. These linearity specifications are based on a 20Hz output rate using a 32.768kHz crystal.
 5. SEC is synchronous external clocking of the data out while SSC is synchronous self-clocking.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.