

TOSHIBA FIELD EFFECT TRANSISTOR SILICON N CHANNEL MOS TYPE

# 2SK2855



UHF BAND AMPLIFIER APPLICATION

## MAXIMUM RATINGS (Ta = 25°C)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Drain-Source Voltage	V <sub>DSS</sub>	10	V
Gate-Source Voltage	V <sub>GSS</sub>	±6	V
Drain Current	I <sub>D</sub>	1.0	A
Drain Power Dissipation	P <sub>D</sub> *	0.5	W
Channel Temperature	T <sub>ch</sub>	150	°C
Storage Temperature Range	T <sub>stg</sub>	-55~150	°C

\*: T<sub>c</sub> = 25°C When mounted on a 1.6mm glass epoxy PCB

## MARKING






## ELECTRICAL CHARACTERISTICS (Ta = 25°C)

CHARACTERISTIC	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Power	P <sub>O</sub>	V <sub>DS</sub> = 6V, f = 849MHz P <sub>i</sub> = 23dBmW	31	—	—	dBmW
Drain Efficiency	η <sub>D</sub>	V <sub>DS</sub> = 6V, f = 849MHz P <sub>i</sub> = 23dBmW, P <sub>O</sub> = 31dBmW	55	—	—	%
Drain-Source Breakdown Voltage	V <sub>(BR)DSS</sub>	V <sub>GS</sub> = 0, I <sub>D</sub> = 1μA	10	—	—	V
Drain Cut-off Current	I <sub>DSS</sub>	V <sub>DS</sub> = 6V, V <sub>GS</sub> = 0	—	—	100	nA
Threshold Voltage	V <sub>th</sub>	V <sub>DS</sub> = 6V, I <sub>D</sub> = 500μA	1.0	1.4	1.8	V
Gate-Source Leakage Current	I <sub>GSS</sub>	V <sub>GS</sub> = 6V, V <sub>DS</sub> = 0	—	—	±100	nA

## CAUTION

This transistor is the electrostatic sensitive device.  
Please handle with caution.

## RF OUTPUT POWER TEST FIXTURE



## CAUTION

These are only typical curves and devices are not necessarily guaranteed at these curves.

**RESTRICTIONS ON PRODUCT USE**

000707EAA

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.  
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.