

SMBT 6427	Si-N-Darl	=2N6427: SMD	35a	-	
SMBT 6428	Si-N	=2N6428: SMD	35a	BC 850	35a
SMBT 6429	Si-N	=2N6429: SMD	35a	BC 850	35a
SMBTA 20	Si-N	=MPSA 20: SMD	35a	BC 846	35a
SMBYT 01-...	Si-Di	=BYT 01-...: SMD	71(6,4mm)	-	
SMBYT 03-...	Si-Di	=BYT 03-...: SMD	71(8mm)	-	
SMBYW 02-...	Si-Di	SMD, S, 50...200V, 2A, <35ns	71(6,4mm)	-	
SMBYW 04-...	Si-Di	SMD, S, 50...200V, 4A, <35ns	71(6,4mm)	-	
SML 1 Q3...	Si-Di	S, TV, 300V, 1A, <80ns	31a	(BYD 33 M)	31a
SML 3 Q3...	Si-Di	S, TV, 300V, 3A, <50ns	31a	(BYW 95 C)	31a
SMP 4 N60	MOS-N-FET-e	V-MOS, 600V, 4A, 75W, <2Ω(2A), <37/95ns	17p	BUK 455/600	17p
SMT 301	Si-N	=BC 546		BC 546	7a
SMV 700	C-Di	=BB 103		-	
SMV 704	C-Di	=BB 203		-	
SMV 709	C-Di	=BA 124		-	
SMV 751	C-Di	=BA 124	7d	-	

SN

SN 54xx...	TTL-Logic	Standard TTL-Logic 54...-Serie		-	
SN 74xx...	TTL-Logic	Standard TTL-Logic 74...-Serie		-	
SN 74LSxx...	TTL-Logic	Standard TTL-Logic 74...-Serie		-	
SN 113	Si-Di	=1N4007: 1600V	31a	BY 228	31a
SN 695-16	Ge-P	=AF 125	5k	AF 239 S	5g
SN 5400....	TTL-Logic	Standard TTL-Logic 54xx-Serie		-	
SN 6157	Si-P		7a	BC 556	7a
SN 7231	Si-N		7a	BC 546	7a
SN 7400....	TTL-Logic	Standard TTL-Logic 74xx-Serie		-	
SN 16227(N)	LIN-IC	CTV, RGB-Matrix	14-DIP	-	**
SN 16848 A,B(N)	LIN-IC	=TDA 2620	16-DIP	-	**
SN 16861(G)(N)	LIN-IC	=TDA 2630	16-DIP	-	**
SN 16862(AN,NG)	LIN-IC	=TDA 2631	16-DIP	-	**
SN 16881 ND	LIN-IC	=TBA 800	12-QIP+b	TBA 800	12-QIP+b
SN 16885 NM1	IC	US-FB Sender/transmitter	16-DIP	-	
SN 16886 NM1	IC	US-FB Sender/transmitter	16-DIP	-	
SN 16889(P)	LIN-IC	LED-Display-Encoder(lin.)		-	
SN 16921(N)	LIN-IC	=UAA 170	16-DIP	-	
SN 16922 ND	LIN-IC	=TBA 810S	12-QIP+b	TBA 810 S	12-QIP+b
SN 28845(N)	LIN-IC	=TCA 4500	16-DIP	TCA 4500 A	16-DIP
SN 29717(N)	LIN-IC	Sensor	24-DIP	-	
SN 29744(N)	LIN-IC	=TBA 1440G	16-DIP	-	
SN 29764(A)(N)	LIN-IC	7-Segment-Decoder	16-DIP	-	**
SN 29767	LIN-IC	TV, Video-ZF-AFC	14-DIP	-	
SN 29770(AN,BN)	LIN-IC	Sensor	16-DIP	-	**
SN 29771(AN,BN)	LIN-IC	Sensor	16-DIP	-	**
SN 29772(AN,BN)	LIN-IC	Sensor	16-DIP	-	**
SN 29773(AN,BN)	LIN-IC	Sensor	16-DIP	-	**
SN 29791	LIN-IC	Sensor	16-DIP	-	**
SN 29845(N)	LIN-IC	=TCA 4500A	16-DIP	TCA 4500 A	16-DIP
SN 29848(N)	LIN-IC	=TDA 2620	16-DIP	-	**
SN 29861(N)	LIN-IC	=TDA 2630	16-DIP	-	**
SN 29862(N)	LIN-IC	=TDA 2631	16-DIP	-	**
SN 29920	IC	IR-FB Sender/transmitter	16-DIP	-	
SN 72555	LIN-IC	Timer	8-DIP	NE 555 N	8-DIP
SN 72741 J,N	OP-IC	Uni, Serie 741, ±18V, 0...+70°	14-DIP	-	
SN 72741 L	OP-IC	=SN 72741 J,N: Fig. →	TO-99	741/TO	TO-99 *