

PNP SILICON PLANAR MEDIUM POWER DARLINGTON TRANSISTOR

FXT705

ISSUE 1 – FEB 94


FEATURES

- * 120 Volt V_{CEO}
- * Gain of 3K at $I_C=1$ Amp
- * $P_{tot} = 1$ Watt

APPLICATIONS

- * Lamp, solenoid and relay drivers
- * Replacement of TO126 and TO220 darlington

REFER TO ZTX705 FOR GRAPHS



E-Line
TO92 Compatible

ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	-140	V
Collector-Emitter Voltage	V_{CEO}	-120	V
Emitter-Base Voltage	V_{EBO}	-10	V
Peak Pulse Current	I_{CM}	-4	A
Continuous Collector Current	I_C	-1	A
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	1	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +200	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-140			V	$I_C = -100\mu A, I_E = 0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-120			V	$I_C = -10mA, I_B = 0^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-10			V	$I_E = -100\mu A, I_C = 0$
Collector Cut-Off Current	I_{CBO}			-0.1 -10	μA μA	$V_{CB} = -120V, I_E = 0$ $V_{CB} = -120V, T_{amb} = 100^{\circ}C$
Collector Cut-Off Current	I_{CES}			-10	μA	$V_{CES} = -80V$
Emitter Cut-Off Current	I_{EBO}			-0.1	μA	$V_{EB} = -8V$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-1.3 -2.5	V V	$I_C = -1A, I_B = -1mA^*$ $I_C = -2A, I_B = -2mA^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$			-1.8	V	$I_C = -1A, I_B = -10mA^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$			-1.7	V	$I_C = -1A, V_{CE} = -5V^*$
Static Forward Current Transfer Ratio	h_{FE}	3k 3k 3k 2k		30k		$I_C = -10mA, V_{CE} = -5V^*$ $I_C = -100mA, V_{CE} = -5V^*$ $I_C = -1A, V_{CE} = -5V^*$ $I_C = -2A, V_{CE} = -5V^*$
Transition Frequency	f_T		160		MHz	$I_C = -100mA, V_{CE} = -10V$ $f = 20MHz$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.