





Bridge Rectifiers, Fast Recovery (Continued)

I_O (AMPS)	4.0		6.0		8.0
@ T_A (°C)	50	4.0 @ 25	50	50	50
@ T_C (°C)		8.0 @ 100	100	50	100
I_{FSM} (AMPS)	200	300	150	250	300
CASE					
V_{RRM} (VOLTS)					
100	CBR 4F-L010	CBR 4MF-L010	CBR 6F-010	CBR 6MF-L010	CBR 8MF-L010
200	CBR 4F-L020	CBR 4MF-L020	CBR 6F-020	CBR 6MF-L020	CBR 8MF-L020
400	CBR 4F-L040	CBR 4MF-L040	CBR 6F-040	CBR 6MF-L040	CBR 8MF-L040
600	CBR 4F-L060	CBR 4MF-L060	CBR 6F-060	CBR 6MF-L060	CBR 8MF-L060
800	CBR 4F-L080	CBR 4MF-L080	CBR 6F-080	CBR 6MF-L080	CBR 8MF-L080
1000	CBR 4F-L100	CBR 4MF-L100	CBR 6F-100	CBR 6MF-L100	CBR 8MF-L100

V_F MAX @ I_F	1.3V @ 3.0A	1.3V @ 2.0A	1.3V @ 3.0A	1.3V @ 3.0A	1.3V @ 4.0A
I_R MAX @ V_{RRM}	10 μ A	10 μ A	10 μ A	10 μ A	10 μ A
t_{rr} (100V thru 400V)	200ns	200ns	200ns	200ns	200ns
t_{rr} (600V thru 800V)	300ns	300ns	300ns	300ns	300ns
t_{rr} (1000V)	500ns	500ns	500ns	500ns	500ns



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.