



Bridge Rectifiers, Fast Recovery

(Continued)

I_O (AMPS)	10		25	35
@ T_A (°C)				
@ T_C (°C)	100	60	60	60
I_{FSM} (AMPS)	150	300	350	400
CASE	 CASE CM	 CASE FP		
V_{RRM} (VOLTS)				
100	CBR10F-J010	CBR10F-010P	CBR25F-010P	CBR35F-010P
200	CBR10F-J020	CBR10F-020P	CBR25F-020P	CBR35F-020P
400	CBR10F-J040	CBR10F-040P	CBR25F-040P	CBR35F-040P
600	CBR10F-J060	CBR10F-060P	CBR25F-060P	CBR35F-060P
800	CBR10F-J080			
1000	CBR10F-J100			

V_F MAX @ I_F	1.3V @ 5.0A	1.3V @ 5.0A	1.3V @ 12.5A	1.3V @ 17.5A
I_R MAX @ V_{RRM}	10 μ A	10 μ A	10 μ A	10 μ A
t_{rr} (100V thru 400V)	200ns	200ns	200ns	200ns
t_{rr} (600V thru 800V)	300ns	300ns	300ns	300ns
t_{rr} (1000V)	500ns			



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.