

2N6516

NPN EPITAXIAL SILICON TRANSISTOR

T-29-21

HIGH VOLTAGE TRANSISOTR


- Collector-Emitter Voltage: $V_{CE0} = 300V$
- Collector Dissipation: $P_C(\max) = 625mW$

ABSOLUTE MAXIMUM RATINGS ($T_a = 25^\circ C$)

Characteristic	Symbol	Rating	Unit
Collector-Base Voltage	V_{CBO}	300	V
Collector-Emitter Voltage	V_{CEO}	300	V
Emitter-Base Voltage	V_{EBO}	6	V
Collector Current	I_C	500	mA
Collector Dissipation	P_C	625	mW
Junction Temperature	T_J	150	$^\circ C$
Storage Temperature	T_{stg}	-55 ~ 150	$^\circ C$

- Refer to 2N6515 for graphs

TO-92



1. Emitter 2. Base 3. Collector

ELECTRICAL CHARACTERISTICS ($T_a = 25^\circ C$)

Characteristic	Symbol	Test Conditions	Min	Typ	Max	Unit
* Collector-Emitter Breakdown Voltage	BV_{CEO}	$I_C = 1mA, I_B = 0$	300			V
Collector-Base Breakdown Voltage	BV_{CBO}	$I_C = 100\mu A, I_E = 0$	300			V
Emitter-Base Breakdown Voltage	BV_{EBO}	$I_E = 10\mu A, I_C = 0$	6			V
Collector Cut-off Current	I_{CBO}	$V_{CB} = 200V, I_E = 0$			50	nA
Emitter Cut-off Current	I_{EBO}	$V_{EB} = 5V, I_C = 0$			50	nA
* DC Current Gain	h_{FE}	$I_C = 1mA, V_{CE} = 10V$	30			
		$I_C = 10mA, V_{CE} = 10V$	45			
		$I_C = 30mA, V_{CE} = 10V$	45		270	
		$I_C = 50mA, V_{CE} = 10V$	40		200	
		$I_C = 100mA, V_{CE} = 10V$	20			
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C = 10mA, I_B = 1mA$			0.3	V
		$I_C = 20mA, I_B = 2mA$			0.35	V
		$I_C = 30mA, I_B = 3mA$			0.5	V
		$I_C = 50mA, I_B = 5mA$			1	V
Base-Emitter Saturation Voltage	$V_{BE(sat)}$	$I_C = 10mA, I_B = 1mA$			0.75	
		$I_C = 20mA, I_B = 2mA$			0.85	
		$I_C = 30mA, I_B = 3mA$			0.9	
Collect-Base Capacitance	C_{cb}	$V_{CB} = 20V, I_E = 0$			6	pF
* Current Gain Bandwidth Product	f_T	$f = 1MHz$ $I_C = 10mA, V_{CE} = 20V$ $f = 20MHz$	40		200	MHz
Base Emitter On Voltage	$V_{BE(on)}$	$I_C = 100mA, V_{CE} = 10V$			2	V

- Pulse Test: Pulse Width $\leq 300\mu s$, Duty Cycle $\leq 2\%$



This datasheet has been downloaded from:

www.DatasheetCatalog.com

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.