




T-3/4 Subminiature Lamps

Line No.	Part No. Wire Lead	Part No. Miniature Flanged	Part No. Bi-Pin	Volts	Amps	M.S.C.P.	Filament Type	Life Hours
1	7100	3810	7810	1.5	0.010	0.002	C-2R	10,000
2	7101	3811	7811	1.5	0.015	0.003	C-2R	5,000
3	8534	7121	7111	2.5	0.110	0.060	C-2R	10,000
4	3102	—	—	4.5	0.022	0.018	C-2R	5,000
5	30	—	—	4.5	0.021	0.017	C-2R	5,000
6	8537	8538	7538	5.0	0.015	0.02	C-2R	1,000
7	6803	8587	7113	5.0	0.060	0.03	C-2R	100,000
8	6833	8913	7114	5.0	0.060	0.05	C-2R	100,000
9	6153	6183	7115	5.0	0.060	0.15	C-2R	3,000
10	7133	8828	7116	5.0	0.075	0.09	C-2R	25,000
11	8666	8383	7117	5.0	0.080	0.15	C-2R	15,000
12	7153	8270	7118	5.0	0.115	0.15	C-2R	40,000
13	7102	7123	7119	5.0	0.115	0.20	C-2R	5,000
14	L51	L52	L53	12.0	0.060	0.15	C-2F	16,000
15	L54	L55	L56	14.0	0.050	0.13	C-2F	16,000
16	*L57	*L58	*L59	28.0	0.024	0.10	CC-2F	16,000

*Add 1.4 to MOL





LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.