

SOT223 PNP SILICON PLANAR HIGH VOLTAGE TRANSISTOR

FZTA92

ISSUE 2 – JANUARY 1996 ☺


FEATURES

- * High breakdown voltage

APPLICATIONS

- * Suitable for video output stages in TV sets and switch mode power supplies

COMPLIMENTARY TYPE – FZTA42
PARTMARKING DETAIL – DEVICE TYPE IN FULL



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	-300	V
Collector-Emitter Voltage	V_{CEO}	-300	V
Emitter-Base Voltage	V_{EBO}	-5	V
Base Current	I_B	-100	mA
Continuous Collector Current	I_C	-500	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	2	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-300			V	$I_C = -100\mu A, I_E = 0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-300			V	$I_C = -1mA, I_B = 0^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5			V	$I_E = -100\mu A, I_C = 0$
Collector Cut-Off Current	I_{CBO}			-0.25	μA	$V_{CB} = -200V, I_E = 0$
Emitter Cut-Off Current	I_{EBO}			-0.1	μA	$V_{EB} = -3V, I_C = 0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-0.5	V	$I_C = -20mA, I_B = -2mA$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$			-0.9	V	$I_C = -20mA, I_B = -2mA$
Static Forward Current Transfer Ratio	h_{FE}	25 40 25				$I_C = -1mA, V_{CE} = -10V^*$ $I_C = -10mA, V_{CE} = -10V^*$ $I_C = -30mA, V_{CE} = -10V^*$
Transition Frequency	f_T	50			MHz	$I_C = -10mA, V_{CE} = -20V$ $f = 20MHz$
Output Capacitance	C_{obo}			6	pF	$V_{CB} = -20V, f = 1MHz$

* Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$
For typical characteristics graphs see FMMTA92 datasheet.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.