

COMPUTER DIODE

General Purpose
Switching

JAN & JANTX 1N3064
1N4454; JAN, JANTX & JANTXV 1N4454
JAN, JANTX & JANTXV 1N4454-1
1N4532; JAN, JANTX & JANTXV 1N4532

ABSOLUTE MAXIMUM RATINGS, AT 25°C

Reverse Breakdown Voltage	75V
Peak Working Voltage	50V
Average Output Current, 1N3064	75mA
1N4454,-1	200mA
1N4532	125mA
Surge Current, 1sec 1N3064	0.5A
1N4454,-1	1A
1N4532	0.5A
Operating Temperature Range	-65°C to +176°C
Storage Temperature Range	-65°C to +200°C

FEATURES

- Metallurgical Bond
- Qualified to MIL-S-19500/144
- Planar Passivated Chip
- DO-7, DO-34 or DO-35 Package

DESCRIPTION


Available in DO-7, DO-34 or DO-35 packages. Microsemi offers high temperature metallurgical bond, making these devices useful in high reliability applications.

ELECTRICAL SPECIFICATIONS (at 25°C unless noted)

Type	Reverse Current @ 25°C	Reverse Current @ 150°C	Reverse Breakdown Voltage @ -65°C	Reverse Recovery Time	Capacitance	Forward Voltage	Forward Recovery Voltage	Forward Recovery Time
1N3064 1N4454 1N4454-1 1N4532	0.1µAdc @ V _R = 50V	100µAdc @ V _R = 50V	75Vdc @ I _R = 5µAdc	4ns @ I _F = I _R = 10mAdc R _L = 100Ω c ≤ 3pF	2pF @ V _R = 0Vdc f = 1MHz V _{sig} = 50mV (pk to pk)	1.0Vdc @ I _F = 10mAdc	5.0V (pk) @ I _F = 100mAdc t _r ≤ 0.4ns	30ns I _F = 100mAdc t _r ≤ 0.4ns

MECHANICAL SPECIFICATIONS


J & JTX 1N3064
J, JTX & JTXV 1N4454 & 1N4454-1
J, JTX & JTXV 1N4532



INCHES		MILLIMETERS	
A	.050-.065	1.27-1.65	
B	.080-.120	2.03-3.05	
C	1.0 MIN.-1.5 MAX.	24.0 MIN.-38.1 MAX.	
D	.018-.022	.46-.56	

INCHES		MILLIMETERS	
A	.078-.107	1.98-2.72	
B	.195-.300	4.96-7.62	
C	1.0 MIN.-1.5 MAX.	24.0 MIN.-38.1 MAX.	
D	.018-.022	.46-.56	

DO-34
1N4532



DO-35
1N4454

Microsemi Corp.
Watertown
The diode experts



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.