

CentralTM Semiconductor Corp.

145 Adams Avenue, Hauppauge, NY 11788 USA

Tel: (631) 435-1110 • Fax: (631) 435-1824

Manufacturers of World Class Discrete Semiconductors

2N6548

2N6549

NPN SILICON DARLINGTON TRANSISTORS

JEDEC TO-202 CASE (EBC)

DESCRIPTION

The CENTRAL SEMICONDUCTOR 2N6548 series types are silicon NPN monolithic darlington transistors designed for amplifier and driver applications where high gain at a high collector current is important.

MAXIMUM RATINGS ($T_A=25^\circ\text{C}$ unless otherwise noted)

	SYMBOL		UNIT
Collector-Base Voltage	V_{CB0}	50	V
Collector-Emitter Voltage	V_{CES}	40	V
Collector-Emitter Voltage	V_{CEO}	40	V
Emitter-Base Voltage	V_{EBO}	12	V
Collector Current	I_C	2.0	A
Base Current	I_B	100	mA
Power Dissipation	P_D	2.0	W
Power Dissipation ($T_C=25^\circ\text{C}$)	P_D	10	W
Operating and Storage Junction Temperature	T_J, T_{STG}	-65 TO +150	$^\circ\text{C}$
Thermal Resistance	θ_{JA}	62.5	$^\circ\text{C}/\text{W}$
Thermal Resistance	θ_{JC}	12.5	$^\circ\text{C}/\text{W}$

ELECTRICAL CHARACTERISTICS ($T_A=25^\circ\text{C}$ unless otherwise noted)

SYMBOL	TEST CONDITIONS	2N6548		2N6549		UNIT
		MIN	MAX	MIN	MAX	
I_{CB0}	$V_{CB}=30\text{V}$		100		100	nA
I_{EBO}	$V_{EB}=10\text{V}$		100		100	nA
BV_{CB0}	$I_C=100\mu\text{A}$	50		50		V
BV_{CES}	$I_C=100\mu\text{A}$	40		40		V
BV_{EBO}	$I_E=10\mu\text{A}$	12		12		V
$V_{CE(SAT)}$	$I_C=1.0\text{A}, I_B=2.0\text{mA}$		1.5		1.5	V
$V_{CE(SAT)}$	$I_C=2.0\text{A}, I_B=4.0\text{mA}$		2.0		2.0	V
$V_{BE(SAT)}$	$I_C=1.0\text{A}, I_B=2.0\text{mA}$		2.0		2.0	V
$V_{BE(ON)}$	$V_{CE}=5.0\text{V}, I_C=1.0\text{A}$		2.0		2.0	V
h_{FE}	$V_{CE}=5.0\text{V}, I_C=200\text{mA}$	25,000	150,000	15,000	150,000	
h_{FE}	$V_{CE}=5.0\text{V}, I_C=500\text{mA}$	15,000		10,000		
h_{FE}	$V_{CE}=5.0\text{V}, I_C=1.0\text{A}$	5,000		3,000		
h_{fe}	$V_{CE}=5.0\text{V}, I_C=50\text{mA}, f=1.0\text{kHz}$	20,000		15,000		
f_T	$V_{CE}=5.0\text{V}, I_C=200\text{mA}, f=100\text{MHz}$	100		100		MHz
C_{ob}	$V_{CB}=10\text{V}, I_E=0, f=1.0\text{MHz}$		7.0		7.0	pF



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.